Установка драйвера монитора в ОС Windows 7

1. При подключении монитора к ПК автоматически отображается окно [Параметры экрана]. Щелкните ссылку **Дополнительные параметры**.

00- • «	All Control Panel Items + Display + Screen Resolution - 47 Search Control Panel	2
File Edit View	Tools Help	٦
	Change the appearance of your displays	
	Another display not detected Identify	
	Display: 1. SX-17P DVI	
	Resolution: 1280 × 1024 (recommended)	
	Orientation: Landscape	
	Advanced settings	
	Make text and other items larger or smaller	
	What display settings should I choose?	
	OK Cancel Apply	

ПРИМЕЧАНИЕ. Если окно [Параметры экрана] не открылось автоматически, выберите последовательно **Пуск > Панель управления > Экран > Настройка параметров экрана**.

2. Перейдите на вкладку Монитор и нажмите кнопку Свойства.

Generic PnP Monitor and ATI Radeon HD 4300 Series Properties
Adapter Monitor Troubleshoot Color Management Monitor Type Generic PnP Monitor
Monitor Settings Screen refresh rate:
Utility Hide modes that this monitor cannot display Clearing this check box allows you to select display modes that this monitor cannot display correctly. This may lead to an unusable display and/or damaged hardware.
Colors: True Color (32 bit)
OK Cancel Apply

3. Перейдите на вкладку Драйвер и нажмите кнопку Обновить драйвер.

Generic PnP Monitor Properties				
General Driver Details				
Generic PnP Mo	nitor			
Driver Provider:	Microsoft			
Driver Date:	6/21/2006			
Driver Version:	6.1.7600.16385			
Digital Signer:	Microsoft Windows			
Driver Details To view details about the driver files.				
Update Driver				
Roll Back Driver	If the device fails after updating the driver, roll back to the previously installed driver.			
Disable	Disables the selected device.			
Uninstall	To uninstall the driver (Advanced).			
	OK Cancel			

4. Щелкните ссылку Выполнить поиск драйверов на этом компьютере.

	Undate Driver Software - Generic PnP Monitor	×
Н	ow do you want to search for driver software?	
	Search automatically for updated driver software Windows will search your computer and the Internet for the latest driver software for your device, unless you've disabled this feature in your device installation settings.	
	Browse my computer for driver software Locate and install driver software manually.	
		Cancel

5. Щелкните ссылку Выбрать драйвер из списка уже установленных драйверов и нажмите кнопку Далее.



6. Нажмите кнопку Установить с диска.



7. Нажмите кнопку Обзор.



8. Найдите на компакт-диске папку **Driver** и выберите файл драйвера для используемой модели монитора. Нажмите кнопку **Открыть**.

Locate File				×
Look <u>i</u> n:	🐌 Driver	•	G 🤌 🖻 🛄	
9	Name	*	Date modified	Туре
Recent Places	SX-1/P.inf		1/29/2010 11:49 AM 1/29/2010 12:04 PM	Setup Infc Setup Infc
Desktop				
Libraries				
Network	•			Þ
	File <u>n</u> ame:	*inf		<u>O</u> pen
	Files of type:	Setup Information (*.inf)	-	Cance

9. Нажмите кнопку ОК.



10. Нажмите кнопку Далее.

Update Driver Software - Generic PnP Monitor	
Select the device driver you want to install for thi	is hardware.
Select the manufacturer and model of your hardware disk that contains the driver you want to install, click h	device and then click Next. If you have Have Disk.
✓ Show <u>compatible</u> hardware Model	
SX-17P (Digital)	
This driver is not digitally signed! Tell me why driver signing is important	Have Disk

11. Появится сообщение системы защиты. Щелкните ссылку Все равно установить этот драйвер.



12. Для завершения обновления драйвера нажмите кнопку Закрыть.



13. После этого в окне появится модель монитора. Для закрытия окна [Свойства] нажмите кнопку **Закрыть**.

SX-17P (Digital) Properties	×
General Driver Details	
SX-17P (Digital)	
Driver Provider:	AG Neovo Inc.
Driver Date:	1/29/2010
Driver Version:	1.0.0.0
Digital Signer:	Not digitally signed
Driver Details	To view details about the driver files.
Update Driver	To update the driver software for this device.
Roll Back Driver	If the device fails after updating the driver, roll back to the previously installed driver.
<u>D</u> isable	Disables the selected device.
<u>U</u> ninstall	To uninstall the driver (Advanced).
	Close Cancel

14. Для закрытия окна [Дополнительные параметры] нажмите кнопку ОК.

5X-17P (Digital) and ATI Radeon HD 4300 Series Properties
Adapter Monitor Troubleshoot Color Management
Monitor Type
SX-17P (Digital)
Properties
Monitor Settings
Screen refresh rate:
60 Hertz 🔹
☑ Hide modes that this monitor cannot display
Clearing this check box allows you to select display modes that this monitor cannot display correctly. This may lead to an unusable display and/or damaged hardware.
<u>C</u> olors:
True Color (32 bit) 🔻
OK Cancel Apply

15. Для закрытия окна [Параметры экрана] нажмите кнопку ОК.

			- • ×
() ⊂ ()	All Control Panel Items 🔸 Display 🔸 Screen Resolution 🛛 👻 🍕	Search Control Panel	٩
<u>Eile E</u> dit <u>V</u> iew	Iools Help		
	Change the appearance of your display		
		Dete <u>c</u> t Identify	
	Display: 1. SX-17P (Digital) 🔻		
	Resolution: 1280 × 1024 (recommended) -		
	Orientation:		
		Advanced settings	
	Make text and other items larger or smaller		
	What display settings should I choose?		
	ОК	Cancel Apply	