## So installieren Sie Monitortreiber unter Windows 7

1. Nachdem das Display an den PC angeschlossen wurde, erscheint das [Anzeigeeinstellungen]-Fenster zum Ändern der Darstellung automatisch. Klicken Sie auf **Erweiterte Einstellungen**.

00- <u>*</u> «	All Control Panel Items + Display + Screen Resolution - 4 Search Control Panel
File Edit View	Tools Help
	Change the appearance of your displays
	Another display not detected Identify
	Display: 1. SX-17P DVI 🔹
	Resolution: 1280 × 1024 (recommended) -
	Orientation: Landscape •
	Advanced settings
	Make text and other items larger or smaller
	What display settings should I choose?
	OK Cancel Apply

HINWEIS: Falls das [Anzeigeeinstellungen]-Fenster zum Ändern der Darstellung nicht erscheinen sollte, klicken Sie auf Start > Systemsteuerung > Anzeige > Anzeigeeinstellungen ändern.

2. Klicken Sie auf das **Monitor**-Register, klicken Sie anschließend auf **Eigenschaften**.

Generic PnP Monitor and ATI Radeon HD 4300 Series Properties		
Adapter Monitor Troubleshoot Color Management Monitor Type		
Generic PnP Monitor		
Monitor Settings		
S_creen remesh rate: 60 Hertz ▼		
I Hide modes that this monitor cannot display		
Clearing this check box allows you to select display modes that this monitor cannot display correctly. This may lead to an unusable display and/or damaged hardware.		
Colors: True Color (32 bit) 🔹		
OK Cancel Apply		

3. Klicken Sie auf das Treiber-Register, anschließend auf Treiber aktualisieren.

Generic PnP Monitor Properties			
General Driver Details			
Generic PnP Monitor			
Driver Provider: Microsoft			
Driver Date: 6/21/2006			
Driver Version: 6.1.7600.16385			
Digital Signer: Microsoft Windows			
Driver Details To view details about the driver files.			
Update Driver			
Roll Back Driver If the device fails after updating the driver, roll back to the previously installed driver.			
Disable Disables the selected device.			
Uninstall To uninstall the driver (Advanced).			
OK Cancel			

4. Klicken Sie die Option Auf dem Computer nach Treibersoftware suchen an.

Hov	v do you want to search for driver software?	
•	Search automatically for updated driver software Windows will search your computer and the Internet for the latest driver software for your device, unless you've disabled this feature in your device installation settings.	
•	Browse my computer for driver software Locate and install driver software manually.	
		Cancel

5. Klicken Sie auf die Option Aus einer Liste von Gerätetreibern auf dem Computer auswählen, klicken Sie anschließend auf Weiter.

Browse for driver software	e on your computer			
Search for driver software in this lo	cation:			
E:\Driver		•	B <u>r</u> owse	]
Let me pick from a lis This list will show installed d software in the same categor	t of device drivers on m river software or patible with ry as the device	iy comp	uter e, and all driver	

6. Klicken Sie auf Datenträger.



7. Klicken Sie auf Durchsuchen.



8. Öffnen Sie den **Driver**-Ordner Ihres CD-/DVD-Laufwerkes, wählen Sie die Treiberdatei Ihres Monitormodells. Klicken Sie auf **Öffnen**.

Locate File	-	-		×
Look <u>i</u> n:	\mu Driver	•	G 🤌 🖻 🛄 🗸	
Ca	Name	*	Date modified	Туре
Recent Places	SX-17P.inf		1/29/2010 11:49 AM 1/29/2010 12:04 PM	Setup Infc Setup Infc
Desktop				
Libraries				
Computer				
Network	•	III		•
INELWOIK	File <u>n</u> ame:	*.inf	•	<u>O</u> pen
	Files of type:	Setup Information (*.inf)	-	Cance

9. Klicken Sie auf OK.



10. Klicken Sie auf Weiter.

Selec	t the device driver you want to install for t	his hardware.
M	Select the manufacturer and model of your hardwar disk that contains the driver you want to install, click	re device and then click Next. If you have a k Have Disk.
Shc	w <u>c</u> ompatible hardware	
S)	:- 17P (Digital)	
<u>А</u> Т	his driver is not digitally signed! ell me why driver signing is important	Have Disk

11. Eine Sicherheitsmeldung erscheint. Klicken Sie auf **Diese Treibersoftware** trotzdem installieren.



12. Klicken Sie zum Abschluss der Treiberaktualisierung auf Schließen.



13. Das neue Monitormodel wird nun angezeigt. Schließen Sie das [Eigenschaften]-Fenster mit der **Schließen**-Schaltfläche.

SX-17P (Digital) Properties	SX-17P (Digital) Properties			
General Driver Details				
SX-17P (Digital)				
Driver Provider:	AG Neovo Inc.			
Driver Date:	1/29/2010			
Driver Version:	1.0.0.0			
Digital Signer:	Not digitally signed			
Driver Details	To view details about the driver files.			
Update Driver	To update the driver software for this device.			
Roll Back Driver	If the device fails after updating the driver, roll back to the previously installed driver.			
<u>D</u> isable	Disables the selected device.			
<u>U</u> ninstall	To uninstall the driver (Advanced).			
	Close Cancel			

14. Schließen Sie das übergeordnete [Erweiterte Einstellungen]-Fenster mit der OK-Schaltfläche.

SX-17P (Digital) and ATI Radeon HD 4300 Series Properties
Adapter Monitor Troubleshoot Color Management
SX-17P (Digital)
Properties
Monitor Settings
Screen refresh rate:
60 Hertz 👻
✓ Hide modes that this monitor cannot display
Clearing this check box allows you to select display modes that this monitor cannot display correctly. This may lead to an unusable display and/or damaged hardware.
Colors: True Color (32 bit)
OK Cancel Apply

15. Schließen Sie das [Anzeigeeinstellungen]-Fenster zum Ändern der Darstellung mit der **OK**-Schaltfläche.

🚱 🕞 🖷 «	All Control Panel Items   Display   Screen Resolution	- + Search Control Panel
<u>Eile E</u> dit <u>V</u> iew	<u>T</u> ools <u>H</u> elp	
	Change the appearance of your display	
		Detegt [dentify
	Digplay: 1. SX-17P (Digital) 💌	
	<u>R</u> esolution: 1280 × 1024 (recommended) ▼	
	Qrientation: Landscape	
		Advanced settings
	Make text and other items larger or smaller	
	What display settings should I choose?	
		OK Cancel Apply
	Qrientation: Landscape	Advanced settings